

# Produktinformation

# Universal Measuring and Controlling Device GIA 20 EB



- Universal inputs for standard signals, frequency, Pt100 / Pt1000 and thermocouples
- 2 integrated switching outputs
- Self-monitoring and diagnostic system
- Interface

# **Characteristics**

The GIA 20 EB is a microprocessor-controlled displaying, monitoring and controlling device for universal use.

It has a universal input for standard signals (0..20 mA, 4..20 mA, 0..50 mV, 0..1 V, 0..2 V and 0..10 V), resistance thermometers (Pt100 and Pt1000), thermocouples (type J, K, N, S and T) and frequency (TTL and switch contact). Additionally it provides functions like rotation speed measurement or counter.

The GIA 20 EB is equipped with switching outputs. The output functions can be configured as 2-point controller, min/max alarm, 3point controller, 2-point controller with min/max alarm, etc. The relay state is indicated by 2 additional LEDs below the 7-segment display.

The device identifies impermissible operating states like display or system errors and displays a corresponding error code.

### Technical data

### Measuring inputs

Design type	Input signal	Measuring range	Note
Voltage signal	010 V	010 V	Ri ≥ 300 kOhm
	02 V	02 V	Ri ≥ 10 kOhm
	01 V	01 V	Ri ≥ 10 kOhm
	050 mV	050 mV	Ri ≥ 10 kOhm
Current signal	420 mA	420 mA	Ri = ~ 125 Ohm
	020 mA	020 mA	Ri = ~ 125 Ohm
Resistance	Pt100	-50.0 +200.0 °C	3-wire connection
	Pt100	-200 +850 °C	
	Pt1000	-200 +850 °C	2-wire connection

Thermocouple	NiCr-Ni type K	-270.0 +1350 °C	
	Pt10Rh-Pt type S	-50 +1750 °C	
	NiCrSi-NiSi type N	-270 +1300 °C	
	Fe-CuNi type J	-170 +950 °C	
	Cu-CuNi type T	-270 +400 °C	
Frequency	TTL signal	010 kHz	
	Switching contact NPN	03 kHz	internal pull-up-re- sistor is switched on
	Switching contact PNP	01 kHz	internal pull-down- resistor is switched on
Rotation speed	TTL signal switching con- tact NPN, PNP	09999 U/min	switchable predis- tributor (11000), pulse frequency: max. 600000 pulses/min.
Up / down counter	TTL signal switching con- tact NPN, PNP	09999 U/min	switchable predis- tributor (11000), pulse frequency: max. 10000 pulses/min.

Switching outputs Switching behavior : 2 switch. outputs, not electrically isolated : selectable: low-side, high-side or

push-pullConnection data: low-side: 28 V / 1 A

high-side: Uv / 200 mA

### **Output functions**


Description	Function	
	Output 1	Output 2
2-point controller	digital 2-point controller	
3-point controller	digital 2-point controller	digital 2-point controller
2-point controller with min/max alarm	digital 2-point controller	min/max alarm
Min/max alarm, together		min/max alarm
Min/max alarm, individual	max alarm	min alarm

### Accuracy

: < 0.2 % FS ±1digit
(for 050 mV: < 0.3 % FS ±1digit)
: < 0.5 % FS ±1digit
: < 0.3 % FS ±1digit
(for type S: < 0.5 % FS ±1digit)
: < 0.2 % FS ±1digit


continued on next page

# Produktinformation



Housing	:	glass fibre reinforced Noryl front panel: polycarbonate
Size	:	24 x 48 mm (H x W)
Mounting depth	:	approx. 65 mm
		(incl. screw / clamp terminals)
Panel mounting	:	by VA fixing clamps
Allowed panel thickness	:	from 110 mm
Panel cutout	:	21.7 x 45.0 mm [±0.5 mm] (H x W)

# Connection diagram



### Supply voltages

028	Supply voltage: 928 V DC (Standard)
G12	Design type with electrically isolated supply: 1114 V
G24	Design type with electrically isolated supply: 2227 V

# Ordering code

	1.	2.
GIA20EB	-	-

1.	Supply voltage	
	028	928 V DC (standard)
	G12	electrically isolated supply: 1114 V
	G24	electrically isolated supply: 2227 V
2.	Option	
	00	without option

senseca

### Special design types (upon request)

SA1	<b>Tare and hold function</b> (only for 420 mA input) If the external switch gets closed the display is set to 0 (tare function). As long as the switch stays closed the display is updated. Once the switch is opened the display is frozen (hold function).
SA2	Max value display (only for 420 mA input) The currently measured value is displayed if the external switch is closed. The highest measured value is displayed if the external switch is opened.
SA3	<b>Frequency input for 10100 mV</b> The device provides a frequency input with con- nection possibility for: frequency (10100 mV signals)
SA4	<b>Measuring input 030V</b> The original measuring input 010 V is changed to a measuring input for 030 V signals. All ad- justments for this input have to be done at the menu point 010 V.
SA5	<b>Delayed measured value displaying</b> This special design type can be used to sup- press short-term perturbations of signal normally changing very slowly. This special design type influences only stan- dard signal measurements.

# Accessories

### FS3T

Front panel with 3 operating buttons:

for comfortable configuration, if switching points have to be consistently adjusted, for calling the min and max values, etc.

# GNR 10

Power supply and relay module for supplying a GIA 20 EB (input: 230VAC, power supply for device and transmitter, 2 relay outputs)